

EnOcean Occupancy Sensor Wall Mount >

EnOcean Occupancy Sensors, Wall Mount are wireless and self-powered, providing a cost-effective way to control energy use in unoccupied rooms.

The EnOcean Occupancy Sensors, Wall Mount harvests solar energy from indoor light and uses radio frequency technology to communicate wirelessly with other CoreSync devices, helping building automation systems to reset temperature, turn off lights and control other electrical loads upon detecting that a space has been unoccupied for a set period of time.



FEATURES AND ADVANTAGES

Wireless, interoperable	Communicates with other CoreSync and EnOcean devices and with CoreSync Network Connected Lighting system
Self-powered	Needs no wiring or battery support in a light-harvesting environment
PIR motion sensor with 360° viewing angle	Maximum efficiency in different room settings
Two molded buttons with LED indicators	Ability to link and configure the device locally
Internal tray	Provides power from supplemental coin battery in low-light settings

Dimensions:

Mounting Height:

SPECIFICATIONS

Motion Detector Range:

Mechanical

Power Supply: Indoor light energy harvesting;

Supplemental battery (CR2032) or 2-wire connector for external power or remote

solar cell (optional)

34 ft. (10m) diameter

RF Communications: 902MHz, 868MHz **Transmission Range:** 80 ft. (25m)

Sustaining Charge Time: 3 hours per 24 hours @ 200 lux

25 hours @ 200 lux Charge Time to Full:

Unoccupied Transmission: 10 and 30 minutes since last motion detection

Operating Life in Darkness: 80 hours (after full charge)

EnOcean Equipment Profile (EEP): A5-07-01 Minimum Operating Light: 50 lux (for auto-off only) **Agency Compliance:** 902MHz: Contains FCC: SZV-STM300U

IC: 5713A-STM300U

UKCA, BIS

868MHz: CE Certified, R&TTE Compliant

5.83" H x 2.52" W x 1.8" D (148mm x 64mm x 45mm)

6 to 8 ft. (1.8 to 2.5m) recommended


www.molexces.com/products/coresync/




EnOcean Occupancy Sensor Wall Mount >

ORDERING INFORMATION

Order No.	Description
180997-0005	EnOcean Occ Sensor Wall Mnt 902MHz NA
180997-0105	EnOcean Occ Sensor Wall Mnt 868MHz EU









www.molexces.com/products/coresync/